**Problem 1**) a)  $f(x) = [\text{Rect}(x)\cos(\pi x)] * \text{Comb}(x)$ .

b) First, we find the Fourier transform of one period of the function  $|\cos(\pi x)|$  in the interval  $[-\frac{1}{2}, +\frac{1}{2}]$ , as follows:

$$\int_{-\frac{1}{2}}^{\frac{1}{2}} \cos(\pi x) \exp(-i2\pi sx) dx$$

$$= \int_{-\frac{1}{2}}^{\frac{1}{2}} \frac{1}{2} [\exp(i\pi x) + \exp(-i\pi x)] \exp(-i2\pi sx) dx$$

$$= \frac{1}{2} \int_{-\frac{1}{2}}^{\frac{1}{2}} \exp[i\pi (1 - 2s)x] dx + \frac{1}{2} \int_{-\frac{1}{2}}^{\frac{1}{2}} \exp[-i\pi (1 + 2s)x] dx$$

$$= \frac{\exp[i\pi (\frac{1}{2} - s)] - \exp[-i\pi (\frac{1}{2} - s)]}{i2\pi (1 - 2s)} - \frac{\exp[-i\pi (\frac{1}{2} + s)] - \exp[i\pi (\frac{1}{2} + s)]}{i2\pi (1 + 2s)}$$

$$= \frac{2i \cos(\pi s)}{i2\pi (1 - 2s)} + \frac{2i \cos(\pi s)}{i2\pi (1 + 2s)} = \frac{2 \cos(\pi s)}{\pi (1 - 4s^2)}.$$
(1)

Alternatively, invoking the fact that a single period of f(x) is represented by  $Rect(x) cos(\pi x)$ , we may use the convolution theorem to write

$$\mathcal{F}\{\text{Rect}(x)\cos(\pi x)\} = \text{sinc}(s) * \frac{1}{2}[\delta(s + \frac{1}{2}) + \delta(s - \frac{1}{2})]$$

$$= \frac{\sin[\pi(s + \frac{1}{2})]}{2\pi(s + \frac{1}{2})} + \frac{\sin[\pi(s - \frac{1}{2})]}{2\pi(s - \frac{1}{2})} = \frac{\cos(\pi s)}{\pi(2s + 1)} - \frac{\cos(\pi s)}{\pi(2s - 1)} = \frac{2\cos(\pi s)}{\pi(1 - 4s^2)}.$$
(2)

Considering that the convolution of one period of f(x) with comb(x) produces the periodic function  $|cos(\pi x)|$ , the Fourier transform of f(x) must be the product of comb(s) and the Fourier transform of a single period of f(x), which is given by Eqs.(1) and (2). The Fourier series coefficients of f(x) are thus given by

$$F_n = \frac{2\cos(n\pi)}{\pi(1-4n^2)} = \frac{(-1)^n}{(1-4n^2)(\pi/2)}.$$
 (3)

The Fourier series representation of f(x) is readily found to be

$$f(x) = |\cos(\pi x)| = \sum_{n=-\infty}^{\infty} F_n \exp(i2\pi nx) = \frac{2}{\pi} - \frac{4}{\pi} \sum_{n=1}^{\infty} \frac{(-1)^n \cos(2\pi nx)}{4n^2 - 1}.$$
 (4)